



Fast, high-quality wireless scanning for small office or home office professionals

High-Speed Desktop Scanner

The Brother ADS-3350w Wireless High-Speed Desktop Scanner has a 2.8" colour touchscreen display, double-sided scanning up to 40 ppm, 60-page capacity auto document feeder, advanced security and multiple connectivity options.

- 2.8" colour touchscreen display
- Double-sided scanning up to 40 ppm¹
- Mobile device scanning⁴
- 60-page capacity auto document feeder⁵
- Advanced image optimization features
- Compatible with a wide range of operating systems
- Software bundle included6

ADS-3350w

High-Speed Desktop Scanner



Specifications:

Scan Features	
Scanner Type	Dual Contact Imaging Sensor, Sheet-fed
Scan Speeds (max) ¹	Simplex: Up to 40ppm (black / colour) Duplex: Up to 80ipm (black / colour)
Scan Resolution	Optical: Up to 600 x 600 dpi; Interpolated: Up to 1200 x 1200 dpi
Scan to Capability	PC (Image, Email, OCR, File), Network Folder, E-mail Server ² , SharePoint, FTP, SFTP, USB Memory Stick, Workflows, Cloud Services ^{3,} Mobile Devices ⁴
Advanced Scanning Features	Auto deskew, Auto scan size, Auto image rotation, Continuous scan, Background colour removal, Blank page skip, Colour drop out, Bleed-through removal, Auto start scan, 2 in 1 scan, 1 to 2 scan, Hole punch removal
Connectivity & Compatibility	
Standard Interface	USB 3.0, Ethernet, Wireless
Operating Systems Compatibility	Windows 7 SP1, 8.1, 10 Home, 10 Pro, 10 Education, 10 Enterprise; Windows Server 2012, 2012 R2, 2016, 2019 macOS v10.14.x, v10.15.x, v11, v11.1.x
Scan Drivers Included	TWAIN, WIA, SANE
Scan Driver OS Compatibility	Windows, Mac®, Linux
Supported File Formats	Searchable PDF, Secure PDF, Signed PDF, PDF/A, High Compression PDF, TIFF, Multi-page TIFF, JPEG, BMP, TEXT, Word, Excel, PowerPoint
Cloud Services ³	Google Drive™, OneDrive, Dropbox
Mobile Device Compatibility ⁴	AirPrint®, Brother Mobile Connect
Security	
Security Features	Secure Function Lock, Setting Lock, IP Filter, TLS/SSL, SNMP v3, Enterprise Security (802.1x), Lock Slot
Paper Handling	
Auto Document Feeder Capacity (max.) ⁵	60 pages
Media Types	Plain, Receipts and Photos (carrier sheet recommended), Business Cards, Plastic / Laminated Cards (including embossed), Index Card
Media Weight	11 - 53 lbs.
Media Thickness	0.08mm - 0.28mm (0.003" - 0.01")
Plastic Card Thickness	Embossed: Up to 1.32mm (0.05") Without Embossing: Up to 1.10mm (0.04")
Document Size (min/max)	2.0" - 8.5" (W), 2.0" - 197" (L)
Document Size Plastic Card	2.13" (W), 3.37" (L)
General	
Display	2.8" Color Touchscreen
Customizable Shortcuts	20
Included Software ⁶	Brother Mobile Connect for iOS and Android™ Brother ScanEssentials Lite for Windows Brother iPrint&Scan (desktop) for Windows and Mac® Tungsten PaperPort™ 14SE with OCR for Windows Tungsten Power PDF v3 for Windows
Maximum Daily Duty Cycle ⁷	Up to 6,000 sheets
Warranty	1-year limited warranty

Replacement Supplies & **Optional Accessories:**

PRK-A3001	Replacement Roller Kit	
CS-A3301	CS-A3301 Optional Carrier Sheet (2-pack)	

Setup Information:

Unit Dimensions / Weight	11.7" (W) x 8.5" (D) x 7.5" (H) / 6.3 lbs.
Carton Dimensions / Weight	15.4" (W) x 9.6" (D) x 12.6" (H) / 8.7 lbs.

Carton Contents:

Brother ADS-3350w, USB 3.0 Interface Cable, AC Adapter, Quick Setup Guide



At your side support. One-year limited warranty with free online, live chat, or phone technical assistance for the life of your product.



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.















Colour and monochrome scan speed with all advanced features turned off, Letter at 300dpi.

Requires mail server support.

Requires an Internet connection and an account with desired service.

Requires connection to a wireless network.

Maximum capacity based on using 20 lb. paper.

May require free download.

Maximum ber of scanned pages per day can be used to compare designed durability between like Brother products. For maximum product life, it is best to choose a scanner with a daily duty cycle that exceeds your requirements.