

## HL-L5000D Business Laser Printer with Duplex Printing



### Top Features:

#### Fast Printing for Busy Offices

- Help increase your productivity with a black print speed of up to 42ppm.

#### Flexible Local Connectivity

- Parallel and USB interfaces. Supports DOS printing via Parallel interface and PCL6 emulation.

#### Comprehensive Application Compatibility

- Offers a wide range of print emulations including: PCL6, BR-Script3<sup>†</sup>, IBM Proprinter, Epson FX, PDF version 1.7, and XPS Version 1.0.

#### Flexible Paper Handling

- 250-sheet capacity paper tray adjustable for letter or legal plus a 50-sheet capacity multi-purpose tray for envelopes or alternative media types. Total capacity expandable to 1,340 sheets with optional add-on trays\*.

#### Cost-Efficient Output

- Help reduce running costs due to a high-yield 8,000-page<sup>▼</sup> replacement toner cartridge.

#### Automatic Duplex (Two-Sided) Printing

- Help save paper and create two-sided documents with automatic duplex printing.

#### High-Quality Printing

- Print professional business documents with bold, crisp text and sharp images at up to 1200 x 1200 dpi resolution.

#### Toner Save Mode

- Help save money by using Toner Save mode for your less critical business documents.

#### Easy to Use Control Panel

- Backlit LCD display for easy navigation and menu selection.

#### Customer Support

- 1-year limited warranty with free support for the life of your product.

## Specifications:

<b>Print Technology</b>	Electrophotographic Laser
<b>LCD Display (type/size)</b>	1-line LCD
<b>Paper Size (maximum)</b>	Paper Tray: Up to 8.5" x 14" (legal) Multi-Purpose Tray: 3.0" - 8.5" (W) / 5.0"-14" (L)
<b>Print Speed (maximum)</b>	Up to 42ppm
<b>Time to First Page<sup>▲</sup></b>	Less than 7.2 seconds
<b>Print Resolution (maximum)</b>	Up to 1200 x 1200 dpi
<b>Processor</b>	800 MHz
<b>Emulations</b>	PCL6, BR-Script3*, IBM Proprinter, Epson FX, PDF version 1.7, XPS Version 1.0
<b>Automatic Duplex</b>	Yes
<b>Paper Input Capacity (maximum)<sup>∞</sup></b>	250-sheet capacity paper tray, 50-sheet capacity multi-purpose tray
<b>Optional Input Capacity (maximum)<sup>*∞</sup></b>	1,340 sheets via optional trays
<b>Output Capacity (maximum)<sup>∞</sup></b>	150 sheets (face down), 1 sheet (face up)
<b>Media Types</b>	Plain Paper, Letterhead, Coloured Paper, Recycled Paper, Bond, Labels, Envelopes (up to 10)
<b>Media Weights</b>	Standard Paper Tray: 16 to 32 lbs. Multi-Purpose Tray: 16 to 53 lbs.
<b>Memory (std. / max.)</b>	128MB / 128MB
<b>Standard Interfaces</b>	Hi-Speed USB 2.0, Parallel
<b>Operating Systems Compatibility</b>	Windows <sup>®</sup> : XP Home / XP Professional / XP Professional x64 Edition / Windows Vista <sup>®</sup> / Windows <sup>®</sup> 7, 8, 8.1, 10 / Windows Server <sup>®</sup> 2003 / 2003 R2 (32/64 bit) / 2008 / 2008 R2 / 2012 / 2012 R2 Mac <sup>®</sup> OS X <sup>®</sup> v10.8.5, 10.9.x, 10.10.x Linux
<b>Security Features</b>	Lock Slot, Secure Print
<b>Maximum Monthly Duty Cycle<sup>◊</sup></b>	Up to 50,000 pages/month
<b>Recommended Monthly Volume<sup>*</sup></b>	Up to 3,500 pages/month
<b>Warranty</b>	1-year Limited Warranty
<b>ENERGY STAR<sup>®</sup> Qualified</b>	Yes

## Supplies & Accessories<sup>\*</sup>:

TN-820	Standard Yield Toner Cartridge (approx. 3,000 pages) <sup>▼</sup>
TN-850	High-Yield Toner Cartridge (approx. 8,000 pages) <sup>▼</sup>
DR-820	Drum Unit (approx. 30,000 pages) <sup>▲</sup>
LT-5500	Optional 250-Sheet Capacity Paper Tray
LT-6500	Optional 520-Sheet Capacity Paper Tray

## Carton Contents:

Brother HL-L5000D
Standard Yield Toner Cartridge (3,000 pages) <sup>▼</sup>
DR-820 Drum Unit (30,000 pages) <sup>▲</sup>
Quick Setup Guide
Installation CD-ROM
AC Power Cord

## Setup Information:

<b>UPC Code</b>	012502641742
<b>Unit Dimensions</b>	373 x 388 x 255 mm (WxDxH)
<b>Unit Weight</b>	10.5 Kg
<b>Carton Dimensions</b>	485 x 450 x 371.5 mm (WxDxH)
<b>Carton Weight</b>	12.4 Kg



<sup>▲</sup> From ready mode and standard tray.

<sup>\*</sup> PostScript<sup>®</sup>3 compatible.

<sup>\*</sup> Additional purchase required.

<sup>∞</sup> Maximum capacity based on using 20 lb. paper.

<sup>◊</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products for maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>■</sup> The recommended range of monthly printed pages to achieve the best possible performance and printer life. Printers are intended to handle occasional usage beyond this range with little or no effect. Consistently printing above the recommended print volume, however, may adversely affect the print quality or life of the machine. It is always best to choose a printer with an appropriate recommended print volume to allow for any anticipated increase in printing needs.

<sup>▼</sup> Approximate toner cartridge yield in accordance with ISO/IEC 19752 (letter/A4).

<sup>▲</sup> Approximately 30,000 pages based on 1 page per job and 50,000 pages based on 3 pages per job [letter/A4 simplex pages]. The number of pages may be affected due to a variety of factors including but not limited to media type and media size.