







Mono Laser Printer

HL-L6400pw







Cost efficient

Speed

Versatile

Ideal choice for business

The HL-L6400DW uses super high-yield toner cartridges, fast print speeds up to 52 ppm and auto duplex printing to save money, time and paper. It features flexible paper handling, easy connectivity and a 1.8" LCD display.

- Advanced Security Features
- Built-In Wireless Networking
- Automatic Duplex (Two-Sided) Printing
- Adjustable, Colour Touchscreen Display
- Print From Your Mobile Device
- High-Quality Printing
- Customer Support

HL-L6400_{DW}

Specifications:

Print Technology	Electrophotographic Laser
LCD Display (type/size)	1.8" Colour Touchscreen Display
Paper Size (maximum)	Paper Tray: Up to 8.5" x 14" (legal) Multipurpose Tray: 3.0" - 8.5" (W)/5.0"-14" (L)
Print Speed (maximum)	Up to 52 ppm
Time to First Page▲	Less than 7.5 seconds
Print Resolution (maximum)	Up to 1200 x 1200 dpi
Processor	800 MHz
Emulations	PCL6, BR-Script3*, IBM Proprinter, Epson FX, PDF version 1.7, XPS Version 1.0
Automatic Duplex	Yes
Paper Input Capacity (maximum)∞	520-sheet capacity paper tray, 50-sheet capacity multipurpose tray
Optional Input Capacity (maximum)* $^{\infty}$	2,650 sheets via optional tower tray
Output Capacity (maximum)∞	250 sheets (face down), 10 sheets (face up), 1,050 sheets via optional mailbox
Media Types	Plain Paper, Letterhead, Coloured Paper, Recycled Paper, Bond, Labels, Envelopes (up to 10)
Media Weights	Standard Paper Tray: 16 to 32 lbs. Multipurpose Tray: 16 to 53 lbs.
Memory (std./max.)	512MB/512MB
Standard Interfaces	Wireless 802.11b/g/n, Gigabit Ethernet, Hi-Speed USB 2.0
Operating Systems Compatibility	Windows®: XP Home/XP Professional/XP Professional x64 Edition/Windows Vista®/Windows® 7, 8, 8.1, 10/Windows Server® 2003/2003 R2 (32/64 bit)/2008/2008 R2/2012/2012 R2 Mac® 0S X® v10.8.5, 10.9.x, 10.10.x Linux
Mobile Device Compatibility ⁻	AirPrint™, Google Cloud Print™ 2.0, Brother iPrint&Scan (free downloadable app), Cortado Workplace, Mopria®, Wi-Fi Direct®, NFC+
Web Connect [△]	GOOGLE DRIVE™, ONEDRIVE®, DROPBOX, BOX
Security Features	Secure Function Lock, Enterprise Security (802.1x), Lock Slot, Secure Print, SSL/TLS, IPSec, Integrated NFC Card Reader
Maximum Monthly Duty Cycle [◊]	Up to 150,000 pages/month
Recommended Monthly Volume	Up to 10,000 pages/month
Warranty	1-year limited warranty
ENERGY STAR® Qualified	Yes

Supplies & Accessories*:

TN-820	Standard Yield Toner Cartridge (approx. 3,000 pages)▼
TN-850	High-Yield Toner Cartridge (approx. 8,000 pages)▼
TN-880	Super High-Yield Toner Cartridge (approx. 12,000 pages) [▼]
TN-890	Ultra High-Yield Toner Cartridge (approx. 20,000 pages)▼
DR-890	Drum Unit (approx. 50,000 pages)^
LT-5505	Optional 250-Sheet Capacity Paper Tray
LT-6505	Optional 520-Sheet Capacity Paper Tray
TT-4000	Tower Tray with Stabilizer
MX-4000	4-Bin Mailbox
CH-1000	Card Reader Holder

Carton Contents:

Brother HL-L6400DW	
Super High-Yield Toner Cartridge (12,000 pages)▼	
DR-890 Drum Unit (approx. 50,000 pages) [^]	
Quick Setup Guide	
Installation CD-ROM	
AC Power Cord	

Setup Information:

UPC Code	012502641858
Unit Dimensions	400 x 396 x 288 mm (WxDxH)
Unit Weight	13.3 Kg
Carton Dimensions	497 x 492 x 531 mm (WxDxH)
Carton Weight	15.8 Kg



At your side support. Online or live chat – free support for the life of your printer. At Brother, we want to ensure that your experience with us is exceptional. Visit us at brother.ca where you can download the latest product drivers and software, view product manuals, learn how to get the most out of your product with how-to videos and find answers to frequently asked questions.



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth, www.brotherearth.com

















- From ready mode and standard tray.
 PostScript®3™ compatible.
- Additional purchase required.
- Maximum capacity based on using 20 lb. paper.

 Requires connection to a wireless network. See www.connectprintshare.ca for more details, availability and mobile device compatibility.
- Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
- For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requiremen A Requires an Internet connection and an account with desired service. See www.connectprintshare.ca for details.
- The recommended range of monthly printed pages to achieve the best possible performance and printer life. Printers are intended to handle occasional usage beyond this range with little or no effect. Consistently printing above the recommended print volume, however, may adversely affect the print quality or life of the machine. It is always best to choose a printer with an appropriate recommended
- print volume to allow for any anticipated increase in printing needs.

 Approximate to allow for any anticipated increase in printing needs.

 Approximate to allow for any anticipated increase in printing needs.

 Approximate to allow for any anticipated increase in printing needs.

 Approximately 50,000 pages based on 3 pages per job and 30,000 pages based on 1 page per job and [letter/A4].

 The number of pages may be affected due to a variety of factors including but not limited to media type and media size.
- + The mobile device must have NFC capability and run Android OS 4.0 or later.