



# BG6250E

Gas Powered Portable Generator with Remote and Electric Starting



- Remote Start
- Push-Button Electric Start
- Digital Display
- Auto Voltage Regulation
- Low Oil Shutoff
- Protected Outlets
- Integrated Fuel Gauge
- Never-Flat Wheel Kit
- Startup Battery Wall Charger
- Easy Maintenance
- Remote Pocket

Peak Watts	6,250W
Running Watts	5,000W
Starting	Remote, Electric, Recoil
Sound Level	N/A
Displacement	274cc
Voltage	120/240V
Amperage	41.7A
Run Time (100/25 load)	N/A
Fuel Type	Gasoline
Fuel Tank	5.3 Gal (20L)
Dimensions (LxWxH)	25 x 26 x 22 in
Weight	128 lbs

**5 YEAR**  
LIMITED WARRANTY

L14-30	5-20	5-20
--------	------	------