














BG11500E





Gas Powered Portable Generator with Remote and Electric Starting



- 
Remote Start
- 
Push-Button Electric Start
- 
Digital Display
- 
Auto Voltage Regulation
- 
Low Oil Shutoff
- 
Protected Outlets
- 
Integrated Fuel Gauge
- 
Never-Flat Wheel Kit
- 
Startup Battery Wall Charger
- 
Easy Maintenance
- 
Remote Pocket

Peak Watts	11,500W
Running Watts	9,000W
Starting	Remote, Electric, Recoil
Sound Level	N/A
Displacement	457cc
Voltage	120/240V
Amperage	75.0A
Run Time (100/25 load)	5.0 / 12.0 hrs
Fuel Type	Gasoline
Fuel Tank	6.6 Gal (25L)
Dimensions (LxWxH)	30 x 27 x 26 in
Weight	190 lbs

5 YEAR LIMITED WARRANTY

-  14-50
-  L14-30
-  5-20
-  5-20